

JET Pro+

Jet Motorlu El Kurutma Makinesi Montaj Şeması

Hand Dryer With Jet Motor Installation



1. Makinenin sol ve sağ yanında bulunan 4 adet cıvata sökölür.

Unscrew the left and right side of 4 screws.



2. Makinenin dış gövdesi ok yönünde çekilerek yerinden çıkartılır.

Remove the casing first start from arrow side of the handdryer carefully.



JET Pro+

Jet Motorlu El Kurutma Makinesi Montaj Şeması

Hand Dryer With Jet Motor Installation

3. **X** ile gösterilen noktalardan makinenin alt tabanı 4 vida ile duvara sabitlenir. **A** noktalarının birinden elektrik hattı duvardan makinenin içine çekilir. Tek ucu boşta olan klemense elektrik bağlantısı yapılır.

*firmly screw the basepart from 4 point shown by **X** to the wall.
Pass the electrical cables from the power grid through the hole shown by **A** diameter which is situated above the device's terminal strip. Connect the electrical cables to the hand dryer's terminal strip.*



4. Dikkatlice dış gövde yerine yerleştirilir. Önce alt bölüm sonra üst bölüm yerleştirilerek yerine oturtturulur.

Carefully place the casing on the base of the device. To do so place it over the base with a slight decline from bottom to top.

